Display = 195 [7 11/16"]

Cutout = 180 [7 1/8"]

Hole center = 174 [6 7/8"]

Display = 130 [5 1/8"]

Cutout = 124 [4 7/8"]

Hole center = 118 [4 5/8"]

Drill 6mm (0.24 in) hole in 4 corners

CUTOUT
Remove material from shaded area only

① ② ③ ④

1. Cut hole in mounting surface using mounting template
2. Insert mounting bracket and screw to wall using 4 x supplied self-tapping screws
3. Secure display to mounting bracket by sliding the unit down on the 2 mounting bracket hooks
4. Once bottom of unit is properly seated, carefully push the top of the display until clipped securely in place

Note: go to www.czone.net to download full Touch 7 installation & user manual

IMPORTANT! Ensure this printed mounting template is true to scale before cutting any mounting surface. Use a ruler to check the dimensions are correct